

AQ-102LV Arc flash protection



AQ-102LV is a sophisticated microprocessor-based arc flash protection unit for arc light detection. The AQ-102LV has connectors for up to three (3) fiber sensors. AQ-102LV acts as a sub-unit to an AQ-110x in an AQ-100 arc protection system. It can also function as a stand-alone in light-only systems. AQ-102LV is designed to minimize the damage caused by an arcing fault (arc flash) by tripping the circuit breaker that sources the fault current. The complete system self-supervision function of AQ-102LV provides the highest level of dependability by continuously monitoring all internal system functions as well as external connections.

Features:

- A wide range for the power supply (18...72 V DC or 92...265 V AC/DC)
- A maximum of 3 fiber loop sensors
- 4 trip relays
- 1 system failure relay
- 1 fast binary output
- 2 fast binary inputs
- 1 multifunction push button
- Non-volatile memory
- 11 indication LEDs

Technical Data

PROTECTION

Light (L>)

Circuit breaker failure protection (50BF/52BF)

Trip time when using mechanical trip relays: 7 ms*

Reset time (arc light stage): 2 ms

Protection operational after power up: 88 ms

*) total trip time when using arc light (L>) or when using arc light (L>) and phase/earth overcurrent (I>) from an AQ-110x unit

I/O

Applicable sensors

AQ-06 plastic fiber sensor (3...40 m) (optional)

AQ-07 glass fiber sensor (3-50 m length) (optional)

AQ-08 glass fiber sensor (3...15 m) (optional)

Trip relays (T1, T2, T3, T4)

3 NO + 1 NC or 4 NO

Rated voltage: 250 V AC/DC

Continuous carry: 5 A

Make-and-carry for 3 s: 16 A

Make-and-carry for 0.5 s: 30 A

Breaking capacity DC (when L/R = 40 ms): 40 W; 0.36 A at 110 V DC

Contact material: AgNi 90/10

Binary output (BO1)

Number of outputs: 1

Rated voltage: +24 V DC

Maximum rated current: 20 mA

Binary inputs (BI1, BI2)

Number of inputs: 2

Threshold voltage: 24 V DC

Rated voltage: 250 V

Rated current: 3 mA

Power supply

Auxiliary power supply: 92...265 V AC/DC

Auxiliary power supply: 18...72 V DC (optional)

Maximum interruption: 100 ms

Maximum power consumption: 5 W

Standby current: 90 mA

HMI

11 indication LEDs

Multifunction push button (SET)

Autoconfiguration

Indication reset

System check

SELF-SUPERVISION

Sensors and wiring

Binary I/O

Trip coil

Power supply

Internal voltages

Settings

SYSTEM CONNECTIVITY

AQ-200 series

AQ-300 series

AQ-100 series

ACCESSORIES

AX016 Wall mounting bracket

Application Drawing

